



CT-337

SMART CURRENT CLAMP METER

WITH AUTOMATIC MEASUREMENT SELECTION

FEATURING IMPEDANCE AND CAPACITANCE MEASUREMENT, DIODE TEST, CONTINUITY TEST AND FREQUENCY MEASUREMENT

The measures included in the CT-337 current clamp are designed for the day to day of the electrician installer. It is possible to work in direct (DC) and alternating (AC) current installations, and to measure electronic components.

The automatic measurement type selection prevents mistakes that may damage the instrument when configuring the ranges. This makes the clamp very adequate to be used in vocational training.

The CT-337 clamp can toggle automatically between voltage and current DC/AC automatically adjusting the measurement range; it also has smart auto-selection of the electronic component under test (impedances, capacitors, diodes).

MEASUREMENTS INCLUDED IN THE CT-337 CURRENT CLAMP

- ✓ DC/AC voltage: Up to 1000 V
- ✓ DC/AC current: Up to 1000 A
- ✓ Continuity test: Audible tone
- ✓ Diode test: Audible tone
- ✓ Impedance: Up to 60 MΩ
- ✓ Frequency: Up to 1 kHz
- ✓ Capacitance: Up to 600 µF

SPECIFICATIONS

- ✓ Display: Backlit LCD screen
- ✓ Polarity: Automatic, on-screen indication
- ✓ Smart selection of measurement type and range
- ✓ Dimensions: 94 (W.) x 241 (H.) x 46 (D.) mm
- ✓ Functions: HOLD, MAX HOLD, MIN HOLD
- ✓ Overrange: Built-in overrange protection
- ✓ Power supply: 9 V LR61 battery



CT-337 CURRENT CLAMP 1000 V, 1000 A

| SPECIFICATIONS | CT-337 SMART CURRENT CLAMP 1000 V, 1000 A |
|-------------------------------|--|
| Display | Backlighted LCD screen |
| Display functions | HOLD, MAX HOLD, MIN HOLD |
| Polarity | Automatic: Positive by default and on-screen negative polarity indication |
| Overrange | Built-in overrange protection for Vdc/VAC, Adc/Aac, Capacitance, Frequency and Impedance measurements |
| Analogue to Digital Conversor | 6000 counts |
| Protection class | IEC1010 CAT III 1000 V |
| Max conductor diameter | 32 mm |
| Smart measurement selection | Automatic measurement selection for DC/AC Voltage with auto range and for DC/AC Current. Automatic measurement and range selection for Impedance, Diodes, Continuity or Capacitance. |
| DC voltage | |
| Scales | 600mV / 6V / 60V / 600V / 1000V |
| Resolution | 0.1 mV / 0.001V / 0.01V / 0.1V / 1V |
| Accuracy | 600 mV scale: $\pm(0.8\% \text{ rdg.} + 2 \text{ digits})$ / Other scales: $\pm(0.8\% + 1 \text{ digit})$ |
| Input impedance | 10 M Ω |
| Overload protection | 600 mV scale: $\pm 500 \text{ V}$ / Other scales: $\pm 1000 \text{ V}$ |
| AC voltage | |
| Scales | 6V / 60V / 600V / 1000V |
| Resolution | 0.001V / 0.01V / 0.1V / 1V |
| Accuracy | $\pm(1\% \text{ rdg.} + 2 \text{ digits})$ |
| Input impedance | 10 M Ω |
| Overload protection | 1000 V |
| DC/AC current | |
| Scales | 600A / 1000A |
| Resolution | 0.1A / 1A |
| Accuracy | 600 A scale: $\pm(1.5\% \text{ rdg.} + 15 \text{ digits})$ / Scale 1000 A: $\pm(2\% + 8 \text{ digits})$ |
| Overload protection | 1000 A |
| Diode test | Short/open circuit, pass/fail test |
| Continuity test | Audible tone when the impedance value is below 20 Ω |
| Capacitance | |
| Scales | 6nF / 60nF / 600nF / 6 μ F / 60 μ F / 600 μ F |
| Resolution | 0.001nF / 0.01nF / 0.1nF / 0.001 μ F / 0.01 μ F / 0.1 μ F |
| Accuracy | $\pm(3\% \text{ rdg.} + 5 \text{ digits})$ |
| Frequency | From 40 Hz to 1kHz (resolution 0.001 kHz). Accuracy $\pm(0.5\% \text{ rdg.} + 2 \text{ digits})$ |
| Impedance | |
| Scales | 600 Ω / 6k Ω / 60k Ω / 600k Ω / 6M Ω / 60M Ω |
| Resolution | 0.1 Ω / 0.001k Ω / 0.01k Ω / 0.1k Ω / 0.001M Ω / 0.01M Ω |
| Accuracy | 600 Ω scale: $\pm(1\% \text{ rdg.} + 2 \text{ digits})$ / Other scales: $\pm(1.5\% \text{ rdg.} + 2 \text{ digits})$ |
| Overload protection | $\pm 350 \text{ Vdc}, 350 \text{ VAC}$ |
| Power supply | 9 V LR61 battery |
| Mechanical features | 94 (W.) x 241 (H.) x 46 (D.) mm / 429 g, including battery |
| Included accessories | Test leads, Carrying pouch |

DESIGN AND SPECIFICATIONS ARE SUBJECT TO CHANGES WITHOUT PRIOR NOTICE 03-23

